# Intimidator Spot 250 Advanced by Chauvet

## Smartfade ML Name : IntimidatorSpt250A

Part of the Extended Library
User Notes:
```
Fixture has on/off switch
Fixture has pan and tilt locks
Set menu option Channel to ADVANCED for this personality
Set menu option Pan Angle to 540 for this personality
Set menu option Tilt Angle to 270 for this personality
```
Colour Mixing: None (255)

| DMX | Fader | Smartfade Slot | Home |
|-----|-------|----------------|------|
| 1 | 2 | Pan | 128 |
| 3 | 2 | Pan fine | 0 |
| 2 | 3 | Tilt | 128 |
| 4 | 3 | Tilt fine | 0 |
| 5 | | Focus time | 0 |
| 6 | 6 | Color Wheel/Scroller/Hue#2 | 0 |
| 7 | 13 | Gobo 1 Select | 0 |
| 8 | 15 | Gobo 1 Rotate | 0 |
| 9 | 10 | Shutter/Strobe | 255 |
| 10 | 1 | Intensity fader | 0 |
| 11 | 29 | User 5 | 0 |
| 12 | 48 | Macro3 | 0 |
| 13 | 33 | FX1 | 0 |
| 14 | 22 | Focus | 0 |

| Dev Command | DMX | Value | Time |
|-------------|-----|-------|------|
| Reset | 11 | 84 | 0 |
| Lamp Off | 11 | 115 | 0 |
| Lamp On | 11 | 123 | 0 |

---

# Intimidator Spot 250 Basic by Chauvet

## Smartfade ML Name : IntimidatorSpt250B

Part of the Extended Library
User Notes:
```
Fixture has on/off switch
Fixture has pan and tilt locks
Set menu option Channel to Basic for this personality
Set menu option Pan Angle to 540 for this personality
Set menu option Tilt Angle to 270 for this personality
```
Colour Mixing: None (255)

| DMX | Fader | Smartfade Slot | Home |
|-----|-------|----------------|------|
| 1 | 2 | Pan | 127 |
| 2 | 3 | Tilt | 127 |
| 3 | 6 | Color Wheel/Scroller/Hue#2 | 0 |
| 4 | 13 | Gobo 1 Select | 0 |
| 5 | 15 | Gobo 1 Rotate | 0 |
| 6 | 10 | Shutter/Strobe | 255 |
| 7 | 1 | Intensity fader | 0 |
| 8 | 29 | User 5 | 0 |
| 9 | 33 | FX1 | 0 |
| 10 | 22 | Focus | 0 |

| Dev Command | DMX | Value | Time |
|-------------|-----|-------|------|
| Reset | 8 | 84 | 0 |
| Lamp Off | 8 | 115 | 0 |
| Lamp On | 8 | 123 | 0 |